

PRODUCT DATASHEET

Type: LAVA-DIMM-LED
Art. Nr.: 40467



Short description

Dimmer for lighting LAVA-LED, suitable for all sizes



Product Description

The radio-controlled dimmer can be used to dim the LAVA-LED lighting. Can be controlled either wired via pushbutton or via the radio hand-held transmitter LAVA-FHS-LED. The dimmer can be used for all LAVA-LED sizes. protection rating: IP 20 Dimensions: 95 x 37 x 20 mm, radio frequency: 868 mHz, maximum output line: 192W, output current: 1 x 8A

ETIM characteristics

Assembly arrangement	Basic element with complete housing	Number of modules (module system)	0
Method of operation	Radio frequency (RF)	RAL-number (similar)	9016
App control via Bluetooth	✗	Nominal voltage	12 12 Volt
Dimming phase cut-on	✓	Control voltage	12 12 Volt
Dimming phase cut-off	✗	Nominal power resistive load	96 192 Watt
Serial dimmer	✗	Nominal power inductive load	96 192 Voltampere
Type of load	Universal	Nominal power capacitive load	96 192 Voltampere
Substation input	✓	Max. switching power LED	0 Watt
Light value memory	✓	Core cross section	1.5 1.5 Square millimetre
Applicable with button	✓	Device width	37 Millimetre
Applicable with movement sensor	✓	Device height	100 Millimetre
Applicable with presence indicator	✓	Device depth	21 Millimetre
Applicable with time switch/timer	✓	Min. depth of built-in installation box	0 Millimetre
Applicable with transmission button	✓		
Applicable with infrared button	✗		
Mounting method	Surface mounted		
Type of fastening	Mounting with screw		
Material	Plastic		
Material quality	Thermoplastic		
Halogen free	✗		
Surface protection	Untreated		
Surface finishing	Matt		
Colour	White		
Transparent	✗		

Created on: 27/11/2023

PRODUCT DATASHEET

Suitable for degree of protection (IP)	IP20
Impact strength	IK01
Connection type	Screwed terminal
Compatible with Apple HomeKit	✗
Compatible with Google Assistant	✗
Compatible with Amazon Alexa	✗
IFTTT support available	✗

Created on: 27/11/2023