


PRODUCT DATASHEET

Type: ET-111A
Art. Nr.: 36758



Short description

Radio receiver, 16A, surface mount



Product Description

The ET-111A radio receiver, in combination with the ET-14A radio room thermostat, enables simple switching on of heating or cooling devices. The frequency range 868 MHz guarantees a large range and optimal connection. The ET-111A switches 16 A and can be mounted on the wall or a flush-mounted box 100/100. Switching current: 16 A, dimensions: 140x54x25 mm, protection rating: IP 20, transmission frequency: 868 MHz, range 100 - 300 m, CE marking.

ETIM characteristics

Suitable for dimmer	×	Number of relays	1
Suitable for pulse button	×	RAL-number (similar)	9010
Suitable for roller shutter switch	×	Radio frequency	868 Megahertz
Suitable for venetian shutter switch	×	Code length (Bit)	0
Suitable for venetian-/roller shutter switch	×	Number of commands	0
Suitable for switch	×		
In housing	✓		
In tube base housing	×		
Printed circuit board/module	×		
Current supply	230 V AC		
Push button mode	×		
Switching mode	✓		
With manual radio transmitter	×		
With radio coding device	×		
With radio controlled push button	×		
Mounting method	Other		
Material	Plastic		
Material quality	Thermoplastic		
Halogen free	✓		
Surface protection	Untreated		
Surface finishing	Matt		
Type of fastening	Other		
Colour	White		
Transparent	×		
Suitable for degree of protection (IP)	IP20		

Created on: 27/11/2023

PRODUCT DATASHEET

Degree of protection (NEMA)	Other
Modulation	FM
Rolling code system	×
Compatible with Apple HomeKit	×
Compatible with Google Assistant	×
Compatible with Amazon Alexa	×
IFTTT support available	×

Created on: 27/11/2023